

## 24VDC LAMP FLASHER

### FEATURES

The PK612A (PK-612A) is a light-duty lamp flasher for DC use.

It is designed for emergency call annunciators or similar use where continuous operation is not necessary.

- DC operation
- Easy installation
- Low power requirement

### SPECIFICATIONS

*Dimensions:* 5.0" High (127 mm)  
2.375" Wide (60 mm)  
2.25" Deep (57 mm)

*Construction:* Rugged extruded aluminum case housing quality electronic components on a printed circuit board.

*Connections:* Screw terminals

*Mounting:* Surface

*Power Req'd:* 24VDC

*Duty:* Light

*Load Current:* 1 amp

### REQUIRED COMPONENTS

CM-800 or CM-900 Series Annunciator

PK-601A Power Supply

PK-2019 Control Unit

SF-117/2B or SF117/2C Emergency Call Switch  
-or -

SF-117/4B or SF117/4C Emergency Call Switch

PS-30A Transformer



### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The lamp flasher shall be **LEE DAN**®/TekTone® PK-612A, or approved equal, and shall provide 24 VDC to flash the lamps on specified TekTone® annunciator control panels and dome lamps.

The PK-612A circuitry shall be housed in a rugged extruded aluminum case. Screw terminals shall be provided for installation wiring.