

UL EMERGENCY PULL STATION

APPLICATION

The SF-340B Emergency Station is for use in any location where activation of an emergency signal is required. All electronic components are mounted on a circuit board. The specially mounted LED is completely sealed in plastic.

Due to the flexibility of its design, the SF-340B may be used as a pull cord emergency station, a pull down activated emergency station, or a staff assist emergency call station. The pull cord supplied may be used for emergency call activation or, if desired, the large 1.1" (28 mm) red pull-down lever may be used.

Dome light and system annunciation vary according to the manner in which the SF-340B is connected.

FEATURES

- UL® 1069 Listed
- Simple and flexible operation
- Call-placed indicator
- Call cancel at point of origin
- Flame-retardant (UL® 94V-0) plastic faceplate
- 1.1" (28 mm) wide pull-down lever

SPECIFICATIONS

Dimensions: Height: 4.5" (114 mm)
Width: 2.8125" (72 mm)
Depth: 1.625" (41 mm)
Projects: 0.6875" (17 mm)
from mounting surface
(including pull-down lever)

Construction: Flame-retardant (UL® 94V-0) plastic faceplate. Switch and electronic components are circuit board mounted.

Connections: Plug-in connectors.

Housing: Single gang ring (IH-357) with square box (IH-358), or exact equal.

REQUIRED COMPONENTS

Tek-CARE® NC-300II Nurse Call System



SF-340B
Emergency Station
(Cord Not Shown)

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

Emergency station shall be TekTone® SF-340B or approved equal as supplied by LEE DAN® Communications, Inc. Operation of emergency signals shall be accomplished by a short pull on the nylon cord or by pulling down on the red lever marked EMERGENCY.

The red call-placed LED indicator shall flash to assure the patient that the call has been placed. Switching mechanism shall consist of a reliable DPDT switch.

The SF-340B shall be UL® 1069 Listed.