

EMERGENCY CALL SWITCH

APPLICATION

The SF154B (SF-154B) Emergency Call Switch features a push button switch with DPDT (double-pole double-throw) contacts which are available via wire pigtail. The switch comes pre-wired with both normally open terminals available individually. The switch has a mechanical eye arrangement inside, which provides for positive indication of activation without the need for external power. The switch features push-on push-off operation. The SF154B is designed as a single-gang ABS plastic panel that fits a standard single-gang electrical box.

FEATURES

- Simple operation and installation
- Attractive, flame retardant ABS plastic panel
- Fits standard single-gang electrical box
- Visual indication of activation

SPECIFICATIONS

Dimensions: Height: 4.5" (115 mm)
Width: 2.8125" (72 mm)
Depth: 1.5" (39 mm)
Projects: 0.8125" (21 mm)
(From mounting surface)

Connections: Flame retardant ABS plastic

Housing: Single-gang ring or box

REQUIRED COMPONENTS

LI-381 Corridor Light
PS-30A Transformer



SF-154B
Call Switch

ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

Emergency Call Switch shall be TekTone® SF-154B or approved equal as supplied by LEE DAN®.

The SF154B shall use a push button switch with DPDT (double-pole double-throw) contacts. The switch shall provide for positive visual indication of activation.

Wiring pigtails shall be provided for connection to both normally open contacts. The switch shall be mounted on an attractive, flame retardant ABS plastic panel which is designed to fit onto a single-gang electrical box.